

PUBLIC ADDRESS, NUMERICAL MATRICES



DZ-MICDESK

Part no. H11395 EAN 3662009024974

Features :

- › Micro desk
- › Zone manager for DZ-MATRIX matrix



PRODUCT PAGE ONLINE

audiophony-pa.com/en/product/dz-micdesk

Manuals, compatible accessories and updates — scan the code or click the address.

Technical specifications

Power supply	24 VDC (powered by the DZ-MATRIX or DZ-EXPAND)
Audio output	0 dBV, balanced, RJ45 connector
Gooseneck microphone (included)	Unidirectional electret condenser microphone
Total harmonic distortion	0.01%
RD Port	Transmits and receives AES3 digital audio data as well as control data to the DZ-MATRIX. RJ45 port.
USB Port	Loads WAV/MP3 files for chime sounds
Volume Control	Microphone volume control and zone selector
Zone selector	can address 1 to 64 different zones
Display	shows device information: ID, volume, zone selector
Indicators	signal (green), input peak (red), busy (red), Comm (green)
Finish	steel, black paint
Dimensions (W x D x H)	176 x 61.8 x 162.4 mm
Net weight	0.8 kg

Overview

Up to 64 different zone groups

Each zone can be named and assigned

Volume control

Zone selection

Push-to-talk button

“Emergency” mode for broadcasting a priority emergency message

XLR microphone connector (included) with phantom power

USB port for loading an MP3 chime (max. 4 seconds) into internal memory

RD port for connecting to digital channels 9/10 and 11/12 of the matrix.

Use CAT5e or CAT6 cable up to 100 m long.

Features :

Recommendations — firmware update (June 15, 2026).

All products in the DZ series must be updated to function properly.

To install the updates, all your devices must be connected.

You cannot use the V3.0.0 Setting Software with the DZ-MATRIX V6.3II.

You cannot use the V2.0.8 Setting Software with the DZ-MATRIX V7.1II.

Improvements made.

DZ-MATRIX:

Copy of the DSP settings for linked stereo inputs and outputs

Added a "Clear All" option to the matrix module and enabled one-click matrix creation

Saving and Loading EQ Presets on the Outputs

Adding groups (4 for inputs and 4 for outputs)

Option to select a default preset when the display is turned on

Configuring the IP Address (DHCP or Static IP)

DZ-PAD:

Added "VOL-" and "VOL+" buttons to the OUTPUT page

Add the group page

Compatible accessories



DZ-EXPAND

H11400



DZ-MATRIX

H11393

Photo



Photo



Photo

