

PUBLIC ADDRESS, WALL CONTROLLERS



DZ-PAD

Part no. H11399 EAN 3662009025018

The matrix at your fingertips.

› Touch wall controller for DZ-MATRIX



PRODUCT PAGE ONLINE

audiophony-pa.com/en/product/dz-pad

Manuals, compatible accessories and updates — scan the code or click the address.

Technical specifications

Family	Dz-Matrix
--------	-----------

Overview

The matrix at your fingertips.

The DZ-PAD control unit allows you to control inputs, outputs, scenes, and the system. The system is fully configurable. The names of the inputs and outputs are those created in the DZ-MATRIX software. The unit can be password-protected. On the back, the DZ-PAD has an RD port for connecting to the matrix or the DZ-EXPAND*. The second port allows you to daisy-chain a second controller. Please note that if a second controller is connected, the unit must be powered by 24V DC.

*Use CAT5e or CAT6 cable up to 100 m long.

Installation:

Compatible with a standard junction box (Legrand model)

Dimensions:

Length: 150 mm

Width: 115 mm

Height: 25 mm

Screen:

Size: 4.3 inches

Viewable dimensions: 95 x 54 mm

⚠ Recommendations — firmware update (June 15, 2026).

All products in the DZ series must be updated to function properly.

To install the updates, all your devices must be connected.

You cannot use the V3.0.0 Setting Software with the DZ-MATRIX V6.3II.

You cannot use the V2.0.8 Setting Software with the DZ-MATRIX V7.1II.

Improvements made.

DZ-MATRIX:

Copy of the DSP settings for linked stereo inputs and outputs

Added a "Clear All" option to the matrix module and enabled one-click matrix creation

Saving and Loading EQ Presets on the Outputs

Adding groups (4 for inputs and 4 for outputs)

Option to select a default preset when the display is turned on

Configuring the IP Address (DHCP or Static IP)

DZ-PAD:

Added "VOL-" and "VOL+" buttons to the OUTPUT page

Add the group page

Compatible accessories



DZ-MATRIX

H11393

Photo

