



PACK-UHF410-Lava-F8

Pack UHF receiver + belt transmitter + Lavalier microphone + case

Référence: H10284

409,00 € inc. VAT



UHF410-BASE RECEIVER

- True Diversity Receiver
- Frequency range: UHF 823~832 and 863 ~ 865 MHz
- 40 programmed frequencies with Auto-scan function
- Channel presets: 4 groups, 4 compatible channels in each group
- Channel selection mode: Tact Switch, Auto-Scan, SYNC
- LCD display: frequency, group, channel, RF & AF
- Balanced and unbalanced audio output on XLR and 6.35 mono jack
- Line or Micro level
- Oscillator: PLL Synthesizer
- Frequency stability: $\pm 0.005\%$.
- Modulation mode: FM
- T.H.D. : $< 1\%$ (@ 1 KHz)
- Audio frequency response: 80 Hz to 18 kHz
- Volume control by rotary switch on the front panel
- Squelch adjustment by rotary switch at the back
- Detachable BNC antennas, many accessories available
- Power supply: 12 V DC (adapter included)
- Current consumption : 260mA $\pm$ 10mA
- Dimensions: 200 x 42 x 183 mm (Rackable 19 inches by two)

BELT TRANSMITTER

- True Diversity transmitter
- Frequency band: UHF 863 ~ 865 MHz
- Output power: 10mW (max.)
- 40 channels with Auto-scan function
- LCD display: channel, battery level
- Microphone input on mini XLR
- Gain level -10/0/+10 dB
- Power supply: 2 x AA type 1.5 V batteries (not included)
- Operating time: 10 hours
- Dimensions: 98 x 65 x 25 mm (+ 75 mm for antenna)

LAVALIER MICROPHONE

- Sensitivity: -67 $\pm$ 3 dB
- Directivity: Omnidirectional cardioid
- Frequency response: 50 Hz to 10 KHz
- Maximum operating voltage: 10 V
- Normal operating voltage: 1.5 V
- Power consumption: 0.5 mA max.
- Signal-to-noise ratio: Superior to 58 dB
- Accessories supplied: Cap and hooking pin

- Connection system: Mini XLR
- Dimensions: 37 x 5.5 mm diameter

Caractéristiques

Brand	Audiophony
Family	UHF410