



## BT-626/FRA

Professional 6 channel dimmer/switch pack for 19" rack mounting.

Référence: B04634



- Professional 6 channel dimmer/switch pack for 19" rack mounting
- Maximum load 16A (3680W) per channel with 16A automatic circuit breakers
- Suitable for both inductive and resistive loads
- Can be used to dim incandescent lamps, halogen lamps, low-voltage halogen lamps with power regulation and LED lamps that can be dimmed (load must be > 100W).
- Outlets equipped with French plugs (see barcode label)
- DMX (XLR 3p-+ RJ11) and analog 0/10V (DB9) inputs
- Individual block or channel addressing (soft connection)
- The dimmer/switch mode can be set individually for all channels
- 0-100% fader control for all channels (no external controller required)
- Preheat control to extend lamp life: 0-6%.
- Automatic phase/frequency tracking (45Hz to 63Hz) to improve dimming in difficult conditions.
- LED display to monitor all functions, including internal temperature.
- Mains voltage (200 ~ 240Vac):
  - 3 phases/4 wires: Max. total load = 22kW
  - One phase/2 wires: Max. total load = 9.6kW
- Intelligent thermal protection with automatic fan control.
- Dimensions: 483x88x312mm (19"/2U)
- Weight : 8kg

## Caractéristiques

<b>Brand</b>	Briteq
--------------	--------

# Galerie photos







