



DZ-BOX22

Connection box for microphone or line to be assigned to channels 9/10 or 11/12 of the DZ-MATRIX matrix. Has two balanced analog outputs

Référence: H11396

269,00 € inc. VAT



Connection box for microphone or line to be assigned to channels 9/10 or 11/12 of the DZ-MATRIX matrix.

Has two balanced analog outputs

- 2 analog inputs Micro or line
- Possibility to rename the name of the box on the software
- XLR or RCA connection
- 2 balanced analogue outputs on the rear terminal block
- Microphone sensitivity adjustment
- Phantom power switch
- Signal and clip indicators for inputs and outputs
- RD port to connect to digital channels 9/10, 11/12 of the DZ-MATRIX* matrix.

*Use CAT5e or CAT6 cable with a maximum length of 100 m.

Features:

Inputs

Symmetrical

- Connectors: XLR 3-pin and RCA
- Input impedance : 5.1 K Ω
- THD+N : < 0.01 % typ 20 - 20 kHz, 0 dBu
- Maximum input level: 20 dBu
- Frequency response: 20 Hz ~ 20 kHz +/- 1.5 dB
- Dynamic range: -107 dB max, A-weighted
- Crossover distortion : -87 dB max. Weighting A

Outputs

Symmetrical

Connectors: 2 x 3-pin terminal blocks, 5 mm pitch

Impedance: 240 Ohms

Maximum output level: +20 dBu

Frequency response: 20 Hz ~ 20 kHz +/- 1.5 dB

Dynamic range: -107 dB max, A-weighted

Crossover distortion : -87 dB max. Weighting A

Indicators

Signal: -30 dBu, green

Clip: +17 dBu, red

Ports

Network RD to DZ-MATRIX, RJ45, 100 m maximum of CAT 5E cable (or higher)

Dimensions

W x H x D: 147 x 86 x 47 mm

Caractéristiques

Brand	Audiophony PA
Finish colour	White

Références compatibles



DZ-MATRIX

**1299,00 €
inc. VAT**

Réf: H11393



DZ-EXPAND

**259,00 € inc.
VAT**

Réf: H11400

Galerie photos

