

PORTABLE SOUND SYSTEM, WIRELESS MICROPHONES



GO-Hand-F5

Part no. H11030 EAN 3662009020884

**A professional handheld microphone,
ready for two receiver types.**

- › UHF handheld microphone with 16 frequencies
- › Condenser capsule
- › Compatible with RACER-GoMod Evo and GO-Mono receivers



PRODUCT PAGE ONLINE

audiophony.com/en/product/GO-Hand-F5

Manuals, compatible accessories and updates — scan the code or click the address.

Technical specifications

Type	UHF handheld microphone
Frequency band	F5, 514.000 - 541.750 MHz
Channels	16
Modulation	FM
Max. output power	35 mW
Frequency stability	± 0.005%
Maximum deviation	± 20 kHz
Spurious emissions	below 60 dB under the carrier
Capsule	condenser, unidirectional
Distortion rate	< 1.0% (at 1 kHz)
Tone key frequency	32.768 kHz
Power supply	2x 1.5V AA batteries (3V DC) or 2x 1.2V rechargeable AA cells (2.4V DC)
Current draw	120 mA ± 10 mA
Dimensions	237 x 58 mm (L x D)
Compatible receivers	RACER-GoMod Evo, GO-Mono

Overview

A professional handheld microphone, ready for two receiver types.

The GO-Hand-F5 is a UHF handheld microphone with a unidirectional condenser capsule, designed for precise vocal pickup in presentations, hosting or live music performance. It pairs just as well with a RACER-GoMod Evo module built into a RACER Evo speaker as with a standalone GO-Mono receiver, for use in either a mobile setup or a more traditional installation with a mixing desk.

F5, F6 or F8: how to choose your frequency band.

The GO-Hand is available on three dedicated UHF bands: F5 (514-542 MHz) and F6 (630-660 MHz), both continuous bands, plus F8, which consists of two separate segments (823-832 MHz and 863-865 MHz, the latter corresponding to the European harmonized SRD band). Each band offers 16 selectable frequencies. Since UHF frequency regulations vary by country, it's advisable to check local authorizations before use, particularly outside France. F8 is authorized in most European countries but can be more congested; the F5 and F6 bands offer an alternative wherever local regulations allow them.

Battery life and stability built for the stage.

Powered by two 1.5V AA batteries (or two rechargeable 1.2V cells), the GO-Hand-F5 delivers frequency stability of $\pm 0.005\%$ and distortion below 1.0% at 1 kHz, for faithful vocal reproduction throughout the performance.

Key features:

UHF handheld microphone, F5 band (514-542 MHz)

16 selectable frequencies

Unidirectional condenser capsule

Max. output power: 35 mW

Compatible with RACER-GoMod Evo (RACER Evo speakers) and GO-Mono (standalone receiver)

Power supply: 2x 1.5V AA batteries or 2x 1.2V rechargeable cells

Dimensions: 237 x 58 mm

Compatible accessories



GO-Mono-F5

H11029



RACER-GoModF5

H11411



HF-CLAMP

B08312



RACER80

H11407



RACER120

H11408



RACER250

H11409



RACER80/F5

H11663



RACER120/F5

H11659



RACER250/F5

H11661



RACER-GoModF5 evo

H11668



RACER80 Evo

H11665



RACER250 Evo

H11667