



GO-Head-F5 Pack

Référence: H11146

239,00 € inc. VAT



1 GOMono receiver + 1 GOBody transmitter + 1 GOHead microphone

Receiver: GO-Mono-F5

- 16 UHF frequencies
- UHF frequency band : 514~5432 MHz
- Diversity system for clipless reception
- Adjustable squelch for noise absorption
- Up to 4 receivers can be used simultaneously (4 microphones)
- Adjustable front-panel antennas
- XLR balanced and unbalanced jack outputs
- Rackable in pairs via FREE-RACK (optional)
- Dimensions: 130 x 36 x 92 mm

Transmitter: GO-Body-F5

- UHF 16-frequency pocket transmitter
- UHF frequency ranges 514 ~ 542 MHz
- Mini XLR connector
- Impedance adjustable to line or microphone position
- Operates on two 1.5 V AA batteries
- Dimensions: 65 x 100 x 27 mm

Headset microphone: GOHead

- Mini XLR connector
- Supplied with windscreen and adjustable headband
- Unidirectional condenser condenser
- Frequency response: 100 Hz to 16 kHz
- S/N: > 60 dB
- Impedance: 2.2 kOhms

Caractéristiques

Brand	Audiophony
Family	GO

Galerie photos



 **hitmusic**
Fabrique sensorielle

www.hitmusic.eu/en/