

INTERFACE CHROMATEQ



LD-1024DIN NET

Référence B05032 EAN 5420025650328

Multiple Zone control: 10 different programs can run simultaneously

› 1024 Channel DMX interface & Multizone controller with Ethernet port for Local Area Network (LAN)

› WLAN) that can be easily mounted on a DIN Rail



FICHE PRODUIT EN LIGNE

briteq-lighting.com/fr/ld-1024din-net

Notices, accessoires compatibles et mises à jour — scannez le code ou cliquez sur l'adresse.

Caractéristiques techniques

Protocole	Art-Net, DMX, sACN
Fonction	Application Android, Application iOS, Ethernet, Logiciel, SD

Présentation

1024 Channel DMX interface with ETHERNET port for Local Area Network (LAN, WLAN).

Can be used with the Wi-Light APP from a mobile device (Android + iOS)

1024 output channels when used with a computer

Multizone 1024 output channels when used standalone without computer

30 minutes of Lighting, Audio and Video timeline synchronization with Pro DMX software

Works with the Chromateq Led Player, Pro DMX, Pixxem, Studio DMX and Wi-Light 2 software (included).

Functions and control in standalone mode:

Art-Net and sACN from SD card (including triggers)

Node to decode Art-Net and sACN to DMX (4 universes)

Automatic Real Time Clock triggering for different scenes (day, week, month, year)

External Triggering via 12 smart contacts

RS232 In/Out (16 characters for RS232 triggers, commands or orders)

UDP / Ethernet triggers and commands (from SDK)

Default start scene, scene priority, cross fade time

Total control via the Wi-Light 2 app (Android + iOS)

Multiple Zone control: 10 different programs can run simultaneously

Master/Slave mode for up to 64 interfaces connected together

An optional external infra-red receiver can be connected to the unit (LD-512Kit-IR = IR receiver + 2 remote controllers)

Micro SD card slot for memory extension

Power supply: 5-24V, 0.2A input or 5V DC via USB-C

Accessoires compatibles



LD-512KIT-IR

B05011

Photo



Photo

