



LD-1024EASY+

1024 Channel DMX interface & Multizone controller.

Référence: B05018

- 1024 Channel DMX interface
 - 1024 output channels when used with a computer
 - Multizone 1024 output channels when used standalone without computer (max 6000 steps and 512 scenes max when 512 channels are used)
- 4Mb internal memory and external SD Card reader (extended memory for all type of Micro SD card)
- 16 bits channels management in standalone
- RS232 triggers for standaloneDMX
- input trigger standalone
- 30 minutes of Lighting, Audio and Video timeline synchronization with Pro DMX software
- Integrated DMX splitter (2 outputs)
- Works with the Chromateq Led Player and Chromateq Pro DMX software (included)
- Perfect for fixed installations or rental: Create your programs with the computer and store them into the interface. Once this is done, you can use the unit without computer and use the control buttons to activate your programs.
- Functions and control in standalone mode:
 - Automatic Real Time Clock triggering for different scenes (day, week, month, year)
 - External Triggering via 7 contacts
 - Select one of your 80 programs (max) via the 8 switch buttons x 10 selectable pages
 - **Multiple Zone control: 5 different programs can run simultaneously**
 - Program selection via the NEXT and PREVIOUS buttons
 - General dimmer adjustment
 - Speed adjustment of the programs
 - Manual color selection of your customized colors via the 8 trigger buttons
 - Manual color selection of 100 standard colors via the + and - buttons
 - Master/Slave mode for up to 32 interfaces connected together
 - 4Mb internal memory + SD card slot for memory extension
- 3-pin XLR connectors
- Power supply for the use in standalone mode: 9V to 36V via DC connectors, 5V via USB connector (optional)
- An optional external infra-red receiver can be connected to the unit (LD-512Kit-IR = IR receiver + 2 remote controllers)
- For more information about the software : www.chromateq.com

Caractéristiques

Marque	Briteq
Protocole	Art-Net, DMX, MIDI

Galerie photos





File Tools Help 00:00:00

Device 1 | LP 512 SA

Device: Device 1 | LP 512 SA

Master / Slave: Master

In / Out Config: DMX 1 Out

DMX Universe 1: DMX Universe 1

DMX Universe 2:

Default start scene: Scene 1

Apply 16 Bits on channels

Summer time (+1h April) / Winter time (-1h October)

Date / Hour Time: 15 h 43 m

janvier, 2011

dim.	lun.	mar.	mer.	jeu.	ven.	sam.
26	27	28	29	30	31	1
2	3	4	5	6	7	8
9	10	11	12	13	14	15
16	17	18	19	20	21	22
23	24	25	26	27	28	29
30	31	1	2	3	4	5

Update Date and Time

Name	Duration	Properties	Mem.
1 Scene 1	00m 01s 000	00:000 00:00	<input checked="" type="checkbox"/>
2 Scene 7	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
3 Scene 8	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
4 Scene 9	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
5 Scene 10	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
6 Scene 11	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
7 Scene 12	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
8 Scene 13	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
9 Scene 14	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
10 Scene 2	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
11 Scene 3	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
12 Scene 4	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
13 Scene 5	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>
14 Scene 6	00m 00s 000	00:000 00:00	<input checked="" type="checkbox"/>

Triggers

External Contacts:

Next / Prev. activ on the scene

Repeat every: 0 h 0 m

Start schedule: 0 h 0 m End schedule: 0 h 0 m

janvier, 2011

dim.	lun.	mar.	mer.	jeu.	ven.	sam.
26	27	28	29	30	31	1
2	3	4	5	6	7	8
9	10	11	12	13	14	15
16	17	18	19	20	21	22
23	24	25	26	27	28	29
30	31	1	2	3	4	5

janvier, 2011

dim.	lun.	mar.	mer.	jeu.	ven.	sam.
26	27	28	29	30	31	1
2	3	4	5	6	7	8
9	10	11	12	13	14	15
16	17	18	19	20	21	22
23	24	25	26	27	28	29
30	31	1	2	3	4	5

Sunday Monday Tuesday Wednesday Thursday Friday Saturday

Set Stand Alone Mode Save in Memory

Current date 10 1 2011 10 janvier 2011

fevr. mars avr. mai juin juil. août sept. oct. nov. déc. janv.

