INTERFACE CHROMATEQ

LD-512WALL+

Référence B05016 EAN 5420025650168

› 512 Channel DMX interface for fixed architectural purposes



FICHE PRODUIT EN LIGNE

briteq-lighting.com/fr/ld-512wall

Notices, accessoires compatibles et mises à jour — scannez le code ou cliquez sur l'adresse.

Notice d'utilisation (PDF)

Caractéristiques techniques

- Standalone functions : Direct access via the trigger buttons for: Scene, Page, Color, Speed , Dimmer
- 8 trigger buttons to recall max. 80 programmed scenes (8 buttons x 10 pages)
- Direct access to 8 custom colors (or scroll 100 preprogrammed colors via the up & down buttons)
- Speed and dimmer adjustment for each scene
- Automatic Real Time Clock triggering for different scenes (day, week, month, year)
- Automatic scene recovery when the if the power was accidentally cut off
- External Triggering up to 31 contacts (mutiplexed)
- Master/Slave mode for up to 32 interfaces connected together
- USB cable included

Présentation

512 Channel DMX interface for fixed architectural purposes

Can easily be mounted on walls of any surface.

All the connections are on inside the back panel so no wires are visible.

Nice white finish with blue display and blue led buttons for the activated functions

Works with the Chromateq Led Player software. (included)

All the necessary programs can be created via computer and stored into the interface. Once this is done, you only have to press the buttons to activate your programs.

An optional external infra-red receiver can be connected to the unit (LD-512Kit-IR = IR receiver + 2 remote controllers)

For more information about the software: www.chromateq.com

Photo


DC 9~36V In
GND
TRIG A
TRIG B
TRIG C
TRIG D
TRIG E
M/S DATA
M/S CLK
DC 5V Out
GND
IR+
LIGHT+
DMX 2-
DMX 2+
DMX GND
DMX 1-
DMX 1+
LD-512WALL
DMX512 Stand Alone Device
DC In: 5V (usb) / 9~36V (ext.) 0.2A
S/N: 101287
DC 5V.

Photo



Photo

