



COMBO120Evo

Référence: H11657

509,00 € inc. VAT



100 V, 120 W amplifixer-mixer with integrated media player: USB, FM tuner, Bluetooth and DAB+.

The COMBO120Evo is an all-in-one amplifier-mixer designed for professional environments such as restaurants, shops and offices. With 120 W of 100 V line power, it delivers quality sound for medium-sized spaces. This amplifier offers great versatility thanks to its integrated media player, which includes an FM tuner, DAB+ digital radio, Bluetooth and a USB port. This makes it easy to stream content from multiple sources. The outputs feature Euroblock connectors, facilitating fast and secure installation.

Power:

100V : 120 Watts

70V : 120 Watts

4Ω : 120 Watts **Input sensitivity:**

CH 1 : -52 dBV

CH 2 : -10 dBV

CH 3 : -10 dBV

AUX : -10 dBV **Frequency response:**

80 Hz - 16 kHz (± 3 dB)

Signal-to-noise ratio:

CH 1: ≥ 65 dB

CH 2: ≥ 65 dB

CH 3: ≥ 65 dB

AUX: ≥ 75 dB

T.H.D+N :

< 1% @ 1/8 RMS **Equalization:**

BASS: ± 10 dB (at 100 Hz)

TREBLE: ± 10 dB (at 1 kHz) **Output voltages:**

4Ω / 70V / 100V **Power circuit:**

Class D switching power supply **Power supply:**

AC 220-240V, 50/60 Hz

DC 24V **Protections:**

Short-circuit / Open circuit / Thermal / Limiter / Ultrasonic and radio frequency

Connections:

4 MIC / LINE combo plugs

1 AUX input on RCA

1 TEST/ALARM input

1 balanced LINE OUT pre or post fader output

1 coaxial plug for antenna **Controls :**

Input level

Player level

AUX input level

Bass and treble equalization

CH 1 input priority

General level **Cooling:**

By thermo-regulated ventilation

Dimensions:

483 x 281 x 44 mm **Net weight:**

4.9 kg

Caractéristiques

Brand	Audiophony PA
Power	120 W
Function	Bluetooth, DAB+, FM Tuner, USB

Galerie photos



 **hitmusic**
Fabrique sensorielle

www.hitmusic.eu/en/