



## COMBO60Evo

60 W, 100 V amplifier-mixer with integrated media player: USB, FM tuner, Bluetooth and DAB+.

Référence: H11656

**349,00 € inc. VAT**



The COMBO60Evo is a compact, high-performance amplifier designed for demanding professional environments. With its 60W 100V line output, it guarantees clear, even sound diffusion, perfectly suited to spaces such as restaurants, stores and businesses. The versatile COMBO60Evo integrates an advanced multimedia player, enabling broadcasting via several sources: FM tuner, DAB+ digital radio, Bluetooth and USB port. These options offer great flexibility for adapting music to the ambience of your space with ease. Equipped with Euroblock connectors for the outputs, this amplifier ensures a reliable and secure installation, ideal for professional needs.

**Power:**

100V: 60 Watts

70V: 60 Watts

4Ω: 60 Watts

**Input sensitivity:**

MIC: -52 dBV

LINE: -10 dBV

AUX: -10 dBV

Phantom power: -52 dBV / 12 V balanced

**Frequency response:**

80 Hz - 16 kHz ( $\pm 3$  dB)

**Signal-to-noise ratio:**

MIC:  $\geq 65$  dB

CH 1:  $\geq 65$  dB

CH 2:  $\geq 65$  dB

AUX:  $\geq 75$  dB

**T.H.D+N :**

< 1% @ 1/8 RMS

**Equalization:**

BASS:  $\pm 10$  dB (at 100 Hz)

TREBLE:  $\pm 10$  dB (at 1 kHz)

**Output voltages:**

4Ω / 70V / 100V

**Power circuit:**

Class D switching power supply

**Power supply:**

AC 220-240V, 50/60 Hz

DC 24V

**Protections:**

Short-circuit / Open circuit / Thermal / Limiter / Ultrasonic and radio frequency

**Connections:**

2 Combo connectors

1 AUX input on RCA

1 coaxial connector for antenna

**Settings:**

Input level

Player level

AUX input level

Bass and treble equalization

Overall level

**Cooling:**

Convection **Dimensions:**

320 x 220 x 73 mm

**Net weight:**

2.73 kg

## Caractéristiques

<b>Brand</b>	Audiophony PA
<b>Power</b>	60 W
<b>Function</b>	Bluetooth, DAB+, FM Tuner, USB

## Galerie photos

