



## CR25A-COMBO-F5

250 W battery powered portable sound system with Bluetooth and 500 MHz HF system

Référence: H11025



**Entries :**

- 2 XLR/TRS channels on combo plugs (Mic/Line)
- 1 stereo channel on RCA plugs
- 1 Auxiliary channel on 3.5 stereo jack
- 1 Bluetooth connection
- 2 UHF microphones

**Output:** 1 line output on 6.35 TRS jack

**Speaker:** 12 inch speaker + 1.35 inch titanium motor / Total impedance of 4 Ohms

**Power :** Class D amplifier 250W RMS on mains / 150W RMS on battery.

**Response curve:** 55 - 20k Hz

Sound pressure level: 118 dB SPL max

**HF microphone :**

- UHF diversity at 16 selectable frequencies
- Dynamic cardioid handheld microphone
- UHF frequency band 514 ~ 542 MHz - 35 mW

**Player**

- USB or SD card reader and integrated Bluetooth® receiver
- Delivered with infrared remote control

**Bluetooth**

- Bluetooth® receiver integrated in the player
- Type V2.0 AVRCP, for excellent audio transmission quality equivalent to digital

**Settings and indicators :**

- Independent level adjustments for each channel
- Bass and treble equalizer from -12dB to +12dB
- Echo and Delay effects on the microphone channels
- Power and Limit Indicator
- Battery charge indicators

**Finish:** Molded polypropylene enclosure, metal grill. C35 base for stand.

**Dimensions in mm:** 615 x 350 x 395

**Net weight with batteries:** 24.5 kg

**Batteries:** 2 x 18V / 7Ah NP for the system

**Autonomy:** 5 hours on average depending on the volume

**Charging time:** about 8 hours for the two 18V batteries

**Power Management:**

- Visualization of the charge level by LED display. Simultaneous charging and use.
- Automatic cut-off if the level is too low.

## Caractéristiques

<b>Brand</b>	Audiophony
<b>Power</b>	250 W rms
<b>Impedance</b>	4 $\Omega$
<b>Model size</b>	12"
<b>Function</b>	Battery, Bluetooth, Mounting 35 mm, SD, USB, Wireless remote control
<b>Family</b>	CR

## Références compatibles



**Ant F5**

**13,44 € inc.**

**VAT**

Réf: H11022

# Galerie photos





  
**CR25A-COMBO**  
 250W portable system  
 Power : AC 220-240V - 50Hz / DC36V  
 AC 100-120V - 60Hz / DC36V  
 2 x 18V - 7Ah battery  
 Fuse : F2.5AL - 250V  
 FSAL - 300V  
 Serial : 

**CAUTION**  
 ATTENTION  
 DANGER  
 ATTENTION

If the appliance won't be used for more than one week or for a long time, please disconnect the battery, please plug the power cable. It needs about 12 hours for full charge, and the green light will be steady. PLEASE USE ORIGINAL BATTERIES!

Si l'appareil n'a pas été utilisé pendant plus d'une semaine ou si le temps est long, veuillez débrancher la batterie, s'il vous plaît. Il faut environ 12 heures pour une charge complète et la lumière verte sera fixe. MERCI D'UTILISER DES BATTERIES D'ORIGINE.



