



## **CR25A-COMBO-F8**

Portable sound system 12 inches 250 W on battery with 2 UHF microphones and Bluetooth player - 800 MHz range

**Référence:** H10789

**Inputs:**

- 2 XLR/TRS channels on combo plugs (Mic/Line)
- 1 stereo channel on RCA plugs
- 1 Auxiliary channel on 3.5 stereo jack plug
- 1 Bluetooth connection
- 2 UHF microphones

**Outputs:**

1 line output on 6.35 TRS

Loudspeaker: 12" HP + 1.35" titanium motor / Total impedance 4 Ohms

Power: Class D amplifier 250W RMS on mains / 150W RMS on battery.

Response curve: 55 - 20k Hz

Acoustic pressure: 118 dB SPL max

**HF microphone:**

- UHF diversity at 16 selectable frequencies
  - Dynamic cardioid handheld microphone
  - UHF frequency band 823-832 and 863-865 Mhz - 10 mW
- Player:**
- USB key or SD card reader and integrated Bluetooth® receiver
  - Supplied with infrared **Bluetooth®** remote control :
  - Bluetooth® receiver integrated into the player
  - Type V2.0 AVRCP, for excellent audio transmission quality equivalent to digital.

**Controls and indicators:**

- Independent level controls for each channel
- Bass and treble equalizer from -12dB to + 12dB
- Echo and Delay effects on mic channels
- Power and Limit indicators
- Battery charge indicators

**Finish:**

Polypropylene molded enclosure, metal grille. C35 base for stand.

Dimensions in mm: 615 x 350 x 395

Net weight with batteries: 24.5 kg

Batteries: 2 x 18V / 7Ah NP for the

system Autonomy: 5 hours on average, depending on volume

Charging time: approx. 8 hours for the two 18V batteries

**Power management:**

- LED display shows charge level.

Simultaneous charging and use.

- Automatic cut-off if the level is too low.

## Caractéristiques

<b>Brand</b>	Audiophony
--------------	------------

<b>Power</b>	250 W rms
<b>Impedance</b>	4 $\Omega$
<b>Model size</b>	12"
<b>Function</b>	Battery, Bluetooth, Mounting 35 mm, SD, USB, Wireless remote control
<b>Family</b>	CR

## Références compatibles



**CR12A-HEADset**

Réf: H10210



**COV-Racer250**

**145,00 € inc.**

**VAT**

Réf: H10791



