



## DZ-BOX22

Référence: H11396

269,00 € inc. VAT



Connection box for microphone or line to be assigned to channels 9/10 or 11/12 of the DZ-MATRIX matrix. Has two balanced analog outputs

Connection box for microphone or line to be assigned to channels 9/10 or 11/12 of the DZ-MATRIX matrix.  
Has two balanced analog outputs

- 2 analog inputs Micro or line
- Possibility to rename the name of the box on the software
- XLR or RCA connection
- 2 balanced analogue outputs on the rear terminal block
- Microphone sensitivity adjustment
- Phantom power switch
- Signal and clip indicators for inputs and outputs
- RD port to connect to digital channels 9/10, 11/12 of the DZ-MATRIX\* matrix.

\*Use CAT5e or CAT6 cable with a maximum length of 100 m.

### Features:

#### Inputs

Symmetrical

- Connectors: XLR 3-pin and RCA
- Input impedance : 5.1 K $\Omega$
- THD+N : < 0.01 % typ 20 - 20 kHz, 0 dBu
- Maximum input level: 20 dBu
- Frequency response: 20 Hz ~ 20 kHz +/- 1.5 dB
- Dynamic range: -107 dB max, A-weighted
- Crossover distortion : -87 dB max. Weighting A

#### Outputs

Symmetrical

Connectors: 2 x 3-pin terminal blocks, 5 mm pitch

Impedance: 240 Ohms

Maximum output level: +20 dBu

Frequency response: 20 Hz ~ 20 kHz +/- 1.5 dB

Dynamic range: -107 dB max, A-weighted

Crossover distortion : -87 dB max. Weighting A

#### Indicators

Signal: -30 dBu, green

Clip: +17 dBu, red

#### Ports

Network RD to DZ-MATRIX, RJ45, 100 m maximum of CAT 5E cable (or higher)

#### Dimensions

W x H x D: 147 x 86 x 47 mm

### Caractéristiques

<b>Brand</b>	Audiophony PA
<b>Finish colour</b>	White

## Accessoires recommandés



### **DZ-MATRIX**

1299,00 € inc. VAT

Réf: H11393

---

## Galerie photos



---

 **hitmusic**  
Fabrique sensorielle

[www.hitmusic.eu/en/](http://www.hitmusic.eu/en/)