



## DZ-MICDESK

Micro desk, zone manager for the DZ-MATRIX

Référence: H11395

**389,00 € inc. VAT**



- Up to 64 different zone groups
- Each zone can be named and assigned
- Volume control
- Zone selection
- Push to talk button
- "Emergency" mode for broadcasting a priority emergency message
- XLR chassis for microphone (supplied) with Phantom power supply
- USB port for loading an mp3 chime (max. 4 sec. duration) into the internal memory
- RD port for connecting to digital channels 9/10, 11/12 of the matrix.

Use CAT5e or CAT6 cable with a maximum length of 100 m.

#### Features :

- Power supply: 24 VDC (supplied by DZ-MATRIX or DZ-EXPAND)
- Audio output: 0 dBV, balanced, RJ45 connector
- Gooseneck microphone (supplied): unidirectional condenser electret microphone
- Total harmonic distortion: 0.01%
- RD port: transmits and receives AES3 digital audio and control data to the DZ-MATRIX. RJ45 port.
- USB port: uploads WAV / MP3 files for chime sound
- Volume control: controls microphone volume and selects all zones
- Zone selector: can address 1 to 64 different zones
- Display: displays device information: ID, volume, zone selector
- Indicators: signal (green), Input peak (red), Busy (red), Comm (green)
- Finish: steel, black paint
- Dimensions (W x D x H): 176 x 61.8 x 162.4 mm
- Net weight: 0.8 kg

## Caractéristiques

<b>Brand</b>	Audiophony PA
--------------	---------------

## Références compatibles



**DZ-MATRIX**

**1299,00 €  
inc. VAT**

Réf: H11393



**DZ-EXPAND**

**259,00 € inc.  
VAT**

Réf: H11400

## Galerie photos





