CHROMATEQ INTERFACE

LD-1024EASY NET

Part no. B05028 EAN 5420025650281

› 1024 channel DMX interface and multi-zone controller with Ethernet port for local network (LAN

› WLAN)



PRODUCT PAGE ONLINE

briteq-lighting.com/ld-1024easy-net

Manuals, compatible accessories and updates — scan the code or click the address.

Technical specifications

- Multiple zone control : 5 different programs can run simultaneously.
- Program selection via the NEXT and PREVIOUS buttons
- General dimmer setting
- Program speed adjustment
- Manual selection of your custom colors via the 8 trigger buttons

Overview

1024 channel DMX interface with ETHERNET port for local network (LAN, WLAN)

Can be used with the Wi-Light APP from a mobile device (Android + iOS): Video 'Wi-Light 2 APP'.

1024 output channels when used with a computer

Multizone 1024 output channels when used autonomously without computer (max 6000 steps and 512 scenes when 512 channels are used).

Internal memory of 4Mb and external SD card reader (extended memory for any type of Micro SD card)

16-bit channel management in stand-alone mode

RS232 triggers for standaloneDMX

Input trigger standalone

30 minutes of lighting, audio and video timeline synchronization with Pro DMX software

Integrated DMX splitter (2 outputs)

Works with the Chromateq Led Player and the Chromateq Pro DMX software. (included)

Functions and control in stand-alone mode :

Automatic triggering of the clock in real time for different scenes (day, week, month, year)

External triggering via 7 contacts

Selection of one of your 80 programs (max) via the 8 switch buttons x 10 selectable pages

Manual selection of 100 standard colors via the + and - buttons.

Master/slave mode for up to 32 interfaces connected together

4MB internal memory + SD card slot for memory expansion

3-pin XLR connectors

Power supply for stand-alone use: 9V to 36V via DC connectors, 5V via USB connector (optional)

An optional external infrared receiver can be connected to the unit (LD-512Kit-IR = IR receiver + 2 remote controls).

For more information about the software: www.chromateq.com

Compatible accessories



LD-512KIT-IR

B05011