



## Mi6U

6-channel mixer 4 microphone inputs, 2 stereo inputs, 1 Aux output and 1 USB port

Référence: H10911

**149,00 € inc. VAT**



- Frequency response: 20Hz - 20KHz
- THD @ +10dBu: < 0.008%
- Residual noise
- MAIN output: -103dB
- AUX SEND output: -90dB (Mi4U and Mi6U only) - Input gains
- Microphone: 0dB to +45dB
- Line: -20dB to +25dB
  
- Phantom power: +48V DC
  
- Equalization
- HIGH: +/- 15dB @ 12KHz
- LOW: +/- 15dB @ 80Hz Maximum output levels
- MAIN/AUX SEND: +21 dBu
- Headphone output: +18 dBu - Input impedances
- Microphone : 2.3 K Ohms balanced
- Line: 20 K Ohms balanced
- Aux / RCA: 24 K Ohms unbalanced - Output impedances
- MAIN / AUX SEND: 120 Ohms
- REC OUT: 1 K Ohms
- PHONES: 25 Ohms - Meter: -20 dB, -10 dB, 0dB , clip
- Power supply: Transformer AC100~240V 50/60 Hz > DC12V 1A
- Consumption: 11W
- Dimensions (H x W x D): 220 x 210 x 68 mm
- Weight: 0.98 kg

## Caractéristiques

<b>Brand</b>	Audiophony
<b>Function</b>	USB

## Références compatibles



**Mi46U-STAND**

**31,40 € inc.**

**VAT**

Réf: H10987

## Galerie photos



