



## MOJO2200curve

Active system - 1000 W RMS with DSP and Bluetooth TWS. Optional dust cover

Référence: H11175

**1299,00 € inc. VAT**



The MOJO2200curve uses a curve array architecture that provides optimized, controlled diffusion for sound pressure levels of 128dB SPL. With a total of 12 speakers, the satellite has been specially designed to achieve an effective opening of 100° horizontal and 70° vertical.

### **A powerful DSP.**

Bass is provided by a powerful 12" woofer mounted in a bass-reflex cabinet.

The latter houses class-D amplification with full protection, a 4-input mixer with Bluetooth® TWS and a powerful DSP offering the possibility of adjusting the sound to your personal taste. **Feel the power with Bluetooth® TWS.**

Send music from your cell phone to the MOJO2200curve Bluetooth® module.

Thanks to "True Wireless Stereo" technology, it transmits the audio signal to a second MOJO, so you can enjoy stereo mode!

### **Pneumatic coupling bar.**

Installation is simplified thanks to the pneumatic coupling bar, which allows effortless height adjustment and also provides the wired connection between the amplifier and the satellite.

Minimum height: 177 cm

Maximum height: 210 cm **Column**

- Power: 300W RMS - 600W max
- Nominal impedance: 6 Ohms
- Boomer: 3 x 5-inch neodymium
- Tweeter: 9 x 1-inch
- Dispersion: 120° x 70° (HxV)
- Connector: Insert in cabinet
- Dimensions: 188 x 517 x 243 mm
- Net weight: 8 kg

### **Cabinet**

- Power: 500W RMS -1000W max
- Nominal impedance: 4 Ohms
- Boomer: 1 x 12 inches
- Dimensions: 366 x 625 x 541 mm
- Net weight: 27 kg **Set**
- Frequency response 38 - 18,000Hz
- SPL max.

(@1m) 128 dB

### **Amplification**

- Bass stage: 1 x 700W RMS / 1400W Max under 6 Ohms
- Mid/high stage 1 x 300W RMS / 600W Max under 4 Ohms - Inputs:
- CH1: 1 x Combo XLR/Line jack/Micro

- CH2 : 1 x XLR/line jack/mic combo
- CH3: 1 x line jack
- CH4/5: 1 x RCA L/R line + Bluetooth® input - Input impedances
- Microphones 1 & 2: Balanced 40 KHoms
- Line 1 & 2: Balanced 10 KHoms
- Line 3: Balanced 20 KHoms
- Line 4 & 5: Unbalanced 5 KHoms - Outputs:
- 1 Insert on top of cabinet for stellite
- 1 x XLR MIX OUT balanced for output to another system
- 2 x XLR LINE OUT balanced for CH1 and 2 repique.
  
- DSP
- 24 bit (1 in 2 out)
- EQ / Presets / low cut / Delay / Bluetooth® TWS - Level control on each channel + Master
- Subwoofer level control

## Caractéristiques

<b>Brand</b>	Audiophony
<b>SPL max (@1m)</b>	128 dB
<b>Power</b>	800 W rms
<b>Model size</b>	12"
<b>Function</b>	Bluetooth, Bluetooth TWS, DSP
<b>Family</b>	MOJO

## Références compatibles



**COV-  
MOJO2200curve**

**79,00 € inc.  
VAT**

Réf: H11231



**MOJO2200curve\_board**

**129,00 € inc.  
VAT**

Réf: H11232



**WMIC-2.4G TWIN**

**69,00 € inc.  
VAT**

Réf: B08315

## Galerie photos







