



## **PACK-UHF410-Hand-F5**

Référence: H11142

**379,00 € inc. VAT**



UHF receiver pack with handheld microphone and case

### UHF410-Base F5 receiver

- True Diversity receiver
- Frequency range: UHF 514~564 MHz
- 997 programmed frequencies with Auto-scan function
- Channel presets: 8 groups, 16 compatible channels in each group
- Channel selection modes: Manual, Tact Switch, Auto-Scan, SYNC
- LCD display: frequency, group, channel, RF & AF
- Balanced and unbalanced audio output on XLR and 6.35 mono jack
- Line or Micro level
- Oscillator: PLL Synthesizer
- Frequency stability:  $\pm 0.005\%$ .
- Modulation mode: FM
- T.H.D. :  $<1\%$  (@ 1 KHz)
- Audio frequency response: 80 Hz to 18 kHz
- Volume control by rotary switch on the front panel
- Squelch adjustment by rotary switch at the back
- Detachable BNC antennas, many accessories available
- Power supply: 12 V DC (adapter included)
- Current consumption: 260 mA  $\pm$  10 mA
- Dimensions: 200 x 42 x 183 mm (Rackable 19 inches by two)

### Microphone UHF410-Hand F5

- True Diversity transmitter
- Frequency range: UHF 514~564 MHz
- Output power: 35mW max.
- 997 programmed frequencies with SYNC function
- LCD display: Group, channel, battery level
- Power supply: 2 AA 1.5 V batteries (not included)
- Average operating time: 10 hours
- Dimensions: 260 x diam 54 mm

### Caractéristiques

<b>Brand</b>	Audiophony
<b>Family</b>	UHF410

## Galerie photos



---

 **hitmusic**  
Fabrique sensorielle

[www.hitmusic.eu/en/](http://www.hitmusic.eu/en/)