



PACK-UHF410-Hand-F8

Référence: H10282

379,00 € inc. VAT



UHF receiver + handheld microphone + case pack

UHF410-Base RECEIVER

- True Diversity receiver
- Frequency range: UHF 823~832 and 863 ~ 865 MHz
- 40 programmed frequencies with Auto-scan function
- Channel presets: 4 groups, 4 compatible channels in each group
- Channel selection mode: Tact Switch, Auto-Scan, SYNC
- LCD display: frequency, group, channel, RF & AF
- Balanced and unbalanced audio output on XLR and 6.35 mono jack
- Line or Micro level
- Oscillator: PLL Synthesizer
- Frequency stability: $\pm 0.005\%$.
- Modulation mode: FM
- T.H.D. : $<1\%$ (@ 1 KHz)
- Audio frequency response: 80 Hz to 18 kHz
- Volume control by rotary switch on the front panel
- Squelch adjustment by rotary switch at the back
- Detachable BNC antennas, many accessories available
- Power supply: 12 V DC (adapter included)
- Current consumption: 260 mA \pm 10 mA
- Dimensions: 200 x 42 x 183 mm (Rackable 19 inches by two)

UHF410-Hand transmitter

- True Diversity transmitter
- Frequency range: UHF 863 ~ 865 MHz
- Output power: 10 mW (max.)
- 40 programmed frequencies with SYNC function
- LCD display: channel, battery level
- Power supply: 2 x AA 1.5 V batteries (not included)
- Average operating time: 10 hours
- Dimensions: 260 x diam 54 mm

Caractéristiques

Brand	Audiophony
Family	UHF410

Galerie photos



 **hitmusic**
Fabrique sensorielle

www.hitmusic.eu/en/