

POWER DISTRIBUTOR



PD-32SH/ENG-BEL

Part no. B04636 EAN 5420025646369

- › This three-phase power distributor is designed for greater safety in mobile
- › Fixed and rental installations



PRODUCT PAGE ONLINE

briteq-lighting.com/pd-32sh-fra-bel

Manuals, compatible accessories and updates — scan the code or click the address.

Overview

This three-phase power distributor is designed for greater safety in mobile, fixed and rental installations.

Different outtings to choose from for more flexibility (rental companies!) : 6 x 16A grounded power outlets: (2 outlets per phase, 16A blue French/Belgian type power connectors)

1 x 16-PIN industrial rectangular connector: output usable with standard wiring for multipolar rental cables

1 x 19-pin industrial round connector: output usable with standard wiring for multipolar rental cables

Designed and manufactured with the most important international and European safety standards.

Oversized internal conductors for greater reliability!

A 4-pole 32A circuit breaker protects ALL outputs, including the 32A output to the next block in the chain. In case of emergency, all phases AND neutral are disconnected!

The 4-pole 30 mA residual current circuit breaker prevents the risk of electric shock.

Digital voltmeters with 3 digit accuracy per phase

Digital ammeters with 3 digit accuracy per phase

Two C16 automatic circuit breakers (16 A - 1 P + N) per phase

1.5 m long mains input cable (3 x 32 A, 5 wires) with 32 A CEE input plug

(3 P + N + E)

Output connector (3 x 32 A, 5 wires) CEE type (3 P + N + E) bypass

Extremely durable 19"/3U metal case

Photo



Photo

