



PREZONE444

599,00 € inc. VAT

8 channel mixer with 4 independent output zones

- Each entry can be routed to the zone of your choice
- Compatible with WP1 wall controller
- Compatible with the MIC-DESK4 4-zone console



SKU: H10507

Categories: [Mixer Installation](#)

EAN13 : 3662009015811

brand Audiophony PA

- 4 balanced Mic/Line inputs on XLR and Jack 6.35 (TRS)
- 4 stereo inputs on RCA or Mono on 6.35 jack
- 4 balanced link out per zone on Phoenix plug
- Priority microphone on input 1
- Phantom power supply for inputs 1 to 4
- Gain and tone control (3 bands) on channels 1 to 4
- Gain adjustment on all inputs
- Tone control (2 bands) per zone
- RJ45 connector for WP-1 wall controller (remote input) and MIC-DESK desk (remote mic) on each zone
- Mute contact possible on each output
- Zone assignment 1 to 4 on each input channel
- Signal and Peak display on each input channel
- Output level display per zone via 5 LED meter
- Headphone output with volume control (zones and PFL)
- Front monitor speaker
- Access to settings dedicated to the installer (via screwdriver)
- Power supply: 230 V 50/60 Hz and DC 24V
- Power consumption : 30 Watts

- DC24 V emergency power supply with Link Out
- Frequency response: 20 Hz - 20 kHz (+/- 3dB)
- T.H.D (1 kHz nominal power): < 0.1%.
- Equalizer :
- High : +/-15 dB @ 12kHz
- Mid: +/-15 dB @ 2.5 kHz
- Low +/- 15 dB @ 80 Hz
- Dimensions: 320 x 088 x 482 mm
- 19 inch rackable
- Height: 2 units
- Weight : 5 kg

INFORMATIONS COMPLÉMENTAIRES

Brand

Audiophony PA

GALERIE D'IMAGES



