



PREZONE642

10-input mixer and 2-zone preamp - 2 fully independent zones - 6 microphone inputs and 4 line inputs - Level display per zone and per input - 24 V safety power supply

Référence: H9902

549,00 € inc. VAT



- 6 mono Mic/Line inputs on XLR/Jack
- Phantom power supply and priority microphone on inputs 1 and 2
- 4 stereo inputs on RCA or Jack
- Priority input on 6.35 jack
- Zone 1 and 2 mono balanced outputs on XLR
- Zone insert on TRS 6.35 jack
- Balanced SUB output per zone on jack
- REC Output stereo on RCA
- Gain and tone control (3 bands) on microphone inputs
- Gain control on stereo inputs
- Tone control (2 bands) per zone
- SUB volume control by zone
- Access to settings dedicated to the installer (via screwdriver)
- Zone assignment and PFL by way of entry
- Signal and Peak display by LED
- Output level display per zone via 8 LED Vumeter
- Headphone output with volume control (zones and PFL)
- Power supply: 230 V 50/60 Hz
- Power consumption : 16 Watts
- DC24 V emergency power supply with Link Out
- Frequency response: 20 Hz - 20 kHz (+/- 3dB) - T.H.D (1 kHz nominal power) :
< 0,2%
- Equalizer :
- High : +/-12 dB @ 12,5 kHz - Mid : +/-12 dB @ 2,5 kHz - Low +/- 12 dB @ 80 Hz
- Dimensions: 295 x 085 x 482 mm
- 19 inch rackable
- Height: 2 units
- Weight : 5 kg

Caractéristiques

Brand	Audiophony PA
--------------	---------------

Références compatibles



MIC-DESK

85,00 € inc.

VAT

Réf: H9748

Galerie photos

