



RACER120/F5

10-inch 120 W RMS battery-powered portable speaker with USB/SD/BT 5.0 drive + talkover + effect. Includes 1 F5 receiver (Racer-GoModF5) + 2 RACER-GoAnt antennas

Référence: H11659



- Speaker: HP 10" + compression 1" total impedance 4 Ohms
- Power: Amplifier class D 120 W RMS/240 W max.
- Frequency response: 60 - 20 kHz
- Sound pressure: 123 dB SPL max
- USB key and SD card reader, Bluetooth® 5.0 receiver
- Supplied with infrared remote control
- Dimensions in mm: 560 x 360 x 303
- Net weight with batteries: 17.5 kg - **Bluetooth® TWS:**
- Transmission of Bluetooth audio signal in stereo to a second RACER
- Talkover selectable for all microphone channels
- Adjustable room effect

- **Finish:**
- Molded polypropylene enclosure, metal grille
- Storage compartment for 2 microphones and cables
- Retractable handle and transport wheels
- C36 base for stand - **Battery:**
- 2 x DC 12 V 5 Ah for the system, wired in series
- Autonomy : 6 hours on average, depending on volume
- Charging time approx. 8 hours
- "Battery connect" switch for battery backup during storage
- Dimensions: 90 x 100 x 70 mm
- Weight: 1.655 kg

- **Power management:**
- LED display shows charge level
- Simultaneous charging and use
- Automatic cut-off if charge level too low








Caractéristiques

Brand	Audiophony
Power	120 W rms
SPL max (@1m)	123 dB
Model size	10"
Function	Battery, Bluetooth, Bluetooth TWS, Mounting 36 mm, Room effect, SD, Talkover, USB, Wireless remote control

Family

RACER

Références compatibles

 <p>GO-Lava 32,00 € inc. VAT Réf: H9992</p>	 <p>GO-Head 42,00 € inc. VAT Réf: H9991</p>	 <p>GO-Hand-F5 89,00 € inc. VAT Réf: H11030</p>	 <p>GO-Body-F5 69,00 € inc. VAT Réf: H11031</p>	 <p>COV-Racer120 95,00 € inc. VAT Réf: H10208</p>
 <p>RACER-GoModF5 99,00 € inc. VAT Réf: H11411</p>	 <p>RACER-GoAnt 6,00 € inc. VAT Réf: H11412</p>			

Galerie photos







UHF RECEIVER

RACER120
MEDIA PLAYER

Bluetooth

MP3, MP4, MP5, MP6, MP7, MP8, MP9, MP10, MP11, MP12, MP13, MP14, MP15, MP16, MP17, MP18, MP19, MP20, MP21, MP22, MP23, MP24, MP25, MP26, MP27, MP28, MP29, MP30, MP31, MP32, MP33, MP34, MP35, MP36, MP37, MP38, MP39, MP40, MP41, MP42, MP43, MP44, MP45, MP46, MP47, MP48, MP49, MP50, MP51, MP52, MP53, MP54, MP55, MP56, MP57, MP58, MP59, MP60, MP61, MP62, MP63, MP64, MP65, MP66, MP67, MP68, MP69, MP70, MP71, MP72, MP73, MP74, MP75, MP76, MP77, MP78, MP79, MP80, MP81, MP82, MP83, MP84, MP85, MP86, MP87, MP88, MP89, MP90, MP91, MP92, MP93, MP94, MP95, MP96, MP97, MP98, MP99, MP100

CH 1 CH 2 CH 3

LEVEL +

MEMO PLAYER / REC

MIC DIRECT MASTER VOLUME

BASS TREBLE

MASTER EQUALIZER

BATTERY LEVEL

CAUTION

POWER OFF - CHARGE BATTERY CONNECT

audiophony

Do not let your battery discharge!
If the speaker is used for a long time or the red LED is ON, it means the battery is low. Please plug the power cable and turn the BATTERY CONNECT switch ON.

It takes about eight hours for a full charge and the green indicator LED will be on after the charge is complete. PLEASE USE ORIGINAL BATTERIES!

No battery packs are to be disassembled.
Do not open or use any other product components as it may change the CE mark and you may lose the CE mark. Please refer to the instruction of manufacturer's instruction manual.

BATTERY CONNECT switch ON.

Please do not use any other product as it may change the CE mark and you may lose the CE mark. Please refer to the instruction of manufacturer's instruction manual.

PLEASE USE ORIGINAL BATTERIES!

REVERSE POLARITY PROTECTION

2 x 12V 5Ah

DANGER
RISK OF SHOCK OR BURNING
ALWAYS USE CARE

CAUTION
RISK OF SHOCK OR BURNING
ALWAYS USE CARE

CE

MADE IN CHINA

Manufactured by SHIMANO S.A.S.
Davao Science Park
Davao City - PHILIPPINE

PHILIPPINE QUEL LED BATTERIES CONNECTION

