



RACER120/F8

10-inch 120 W RMS battery-powered portable speaker with USB/SD/BT 5.0 drive + talkover + effect. Includes 1 F8 receiver (Racer-GoModF8) + 2 antennas (RACER-GoAnt)

Référence: H11660



- Speaker: HP 10" + compression 1" total impedance 4 Ohms
- Power: Amplifier class D 120 W RMS/240 W max.
- Frequency response: 60 - 20 kHz
- Sound pressure: 123 dB SPL max
- USB key and SD card reader, Bluetooth® 5.0 receiver
- Supplied with infrared remote control
- Dimensions in mm: 560 x 360 x 303
- Net weight with batteries: 17.5 kg - **Bluetooth® TWS:**
- Transmission of Bluetooth audio signal in stereo to a second RACER
- Talkover selectable for all microphone channels
- Adjustable room effect

- **Finish:**
- Molded polypropylene enclosure, metal grille
- Storage compartment for 2 microphones and cables
- Retractable handle and transport wheels
- C36 base for stand - **Battery:**
- 2 x DC 12 V 5 Ah for the system, wired in series
- Autonomy : 6 hours on average, depending on volume
- Charging time approx. 8 hours
- "Battery connect" switch for battery backup during storage
- Dimensions: 90 x 100 x 70 mm
- Weight: 1.655 kg

- **Power management:**
- LED display shows charge level
- Simultaneous charging and use
- Automatic cut-off if charge level too low

Caractéristiques

Brand	Audiophony
Power	120 W rms
SPL max (@1m)	123 dB
Model size	10"
Function	Battery, Bluetooth, Bluetooth TWS, Mounting 36 mm, Room effect, SD, Talkover, USB, Wireless remote control

Family

RACER

Accessoires recommandés



COV-Racer120

**95,00 € inc.
VAT**

Réf: H10208



RACER-GoModF8

**99,00 € inc.
VAT**

Réf: H11410



RACER-GoAnt

**6,00 € inc.
VAT**

Réf: H11412

Galerie photos







audiophony
 Do not let your battery discharge!
 If the speaker is used for a long time or the red LED is ON, it means the battery is low. Please plug the power cable and turn the BATTERY CONNECT switch ON.
 Please check right time for a full charge and the green indicator LED will be on and the charge is complete. PLEASE USE ORIGINAL BATTERIES!

No lithium primary cells battery discharge!
 Do not open or use any other products for repairs as it will change E.C.O.D. which will void the warranty. Do not charge, unless in the presence of professional technician. BATTERY CONNECT switch ON.
 Please use original battery and only use charge compatible with the manufacturer and use original plug-in to be able to charge.
 PLEASE USE ORIGINAL BATTERIES!

REVERSE POLARITY PROTECTION
 2 x 12V 5Ah
DANGER
 RISK OF BATTERY EXPLOSION
 ALL THE TIME
CAUTION
 RISK OF BATTERY BURN
 ALL THE TIME
 CE
 MADE IN CHINA
 Manufactured by SHENZHEN S.L.S.
 Dong Guan City
 GUANGDONG PROVINCE - CHINA
 100% RECYCLED PAPER

