



RACER250/F5

Référence: H11661



12-inch 250 W RMS battery-powered portable speaker with USB/SD/BT 5.0 drive + talkover + effect.
Includes 1 F5 receiver (Racer-GoModF5) + 2 antennas (RACER-GoAnt)

- Speaker: 12" speaker + 1.35" compression driver total impedance 4 Ohms
- Power: Class D amplifier 250 W RMS/500 W max.
- Frequency response: 50 - 20 kHz
- Sound pressure: 125 dB SPL max
- USB key and SD card reader, Bluetooth® 5.0 receiver
- Supplied with infrared remote control
- Dimensions in mm: 614 x 350 x 395
- Net weight with batteries: 22.5 kg - **Bluetooth® TWS:**
- Transmission of Bluetooth audio signal in stereo to a second RACER
- Talkover selectable for all microphone channels
- Adjustable room effect

- Finish:

- Molded polypropylene enclosure, metal grille
- Storage compartment for 2 microphones and cables
- Retractable handle and transport wheels
- C36 base for stand - **Battery:**
- 2 x DC 18 V 7 Ah for the system, wired in series
- Autonomy : 5 hours on average, depending on volume
- Charging time approx. 8 hours
- "Battery connect" switch for battery backup during storage
- Dimensions: 150 x 95 x 97 mm
- Weight: 3.075 kg

- Power management:

- LED display shows charge level
- Simultaneous charging and use
- Automatic cut-off if charge level too low

Caractéristiques

Brand	Audiophony
Power	250 W rms
SPL max (@1m)	125 dB
Model size	12"
Function	Battery, Bluetooth, Bluetooth TWS, Mounting 36 mm, Room effect, SD, Talkover, USB, Wireless remote control
Family	RACER

Accessoires recommandés



RACER-GoModF5

99,00 € inc. VAT
Réf: H11411



RACER-GoAnt

6,00 € inc. VAT
Réf: H11412

Galerie photos



 **hitmusic**
Fabrique sensorielle

www.hitmusic.eu/en/