

WIRELESS MICROPHONES



UHF410-Lava

Part no. H10275 EAN 3662009013466

An invisible mic for a natural on-camera presence.

- › Discreet condenser capsule lavalier mic
- › For UHF410 bodypack transmitters
- › Mini XLR connection



PRODUCT PAGE ONLINE

audiophony.com/en/product/UHF410-Lava

Manuals, compatible accessories and updates — scan the code or click the address.

[User manual \(PDF\)](#)

Technical specifications

Brand	Audiophony
Sensitivity	-42 ± 3 dB
Polar pattern	omnidirectional
Frequency response	50 Hz - 10 kHz
Max operating voltage	10 V
Normal operating voltage	1.5 V
Current draw	0.5 mA max.
Signal-to-noise ratio	above 58 dB
Included accessories	windscreen and mounting clip
Connection	mini XLR
Dimensions	37 mm × Ø 5.5 mm

Overview

An invisible mic for a natural on-camera presence.

The UHF410-Lava is a lavalier microphone, built to plug into the mini XLR input on a UHF410-Body bodypack transmitter. Its small size (37 mm, 5.5 mm diameter) keeps it genuinely discreet once clipped to clothing, ideal for video recording, interviews, or any situation where the mic needs to stay out of sight.

Wide, even pickup.

The condenser capsule, running an omnidirectional pattern, picks up sound evenly from all around the mic, for a natural sound no matter where the speaker's voice is coming from. Frequency response from 50 Hz to 10 kHz, signal-to-noise ratio above 58 dB. A windscreen and mounting clip ship with the mic for attaching it to clothing.

Key features:

Discreet lavalier mic, condenser capsule

Omnidirectional pattern

50 Hz - 10 kHz frequency response

Mini XLR connection, compatible with UHF410-Body transmitters

Windscreen and mounting clip included

Compatible accessories



UHF410-Body-F5
H11028



UHF410-Body-F8
H10273